



# Single-Output: 2000 W GPIB



6671A - 6675A

- Proven reliability
- Increase test throughput with fast up and down programming
- High efficiency
- Low ripple and noise

This series of 2000 watt dc power supplies has the exceptional, proven reliability that test system engineers look for. It also has the unusual combination of high efficiency and low noise operation.

Programming of the dc output and the extensive protection features can be done either from the front panel or using industry standard SCPI commands, via the GPIB. Using the serial link, up to 16 power supplies can be connected through one GPIB address. Test system integration can be further simplified by using the *VXIPlug&Play* drivers. The output voltage and current can also be controlled with analog signals. This is helpful for certain types of noisy environments, and also immediate reactions to process changes.

Lab-bench use is enhanced by the fan-speed control, which minimizes acoustic noise. The extremely low ripple and noise helps the built-in measurement system make extremely accurate current and voltage measurements.

Specifications (at 0° to 55° C unless otherwise specified)	6671A	6672A	6673A	6674A	6675A
<b>Number of outputs</b>	1	1	1	1	1
<b>GPIB</b>	Yes	Yes	Yes	Yes	Yes
<b>Output ratings</b>					
Output voltage	0 to 8 V	0 to 20 V	0 to 35 V	0 to 60 V	0 to 120 V
Output current	0 to 220 A	0 to 100 A	0 to 60 A	0 to 35 A	0 to 18 A
<b>Programming accuracy at 25° C ±5° C</b>					
Voltage	0.04% + 8 mV	20 mV	35 mV	60 mV	120 mV
Current	0.1% + 125 mA	60 mA	40 mA	25 mA	12 mA
<b>Ripple and noise</b>					
from 20 Hz to 20 MHz					
Voltage rms	650 µV	750 µV	800 µV	1.25 mV	1.9 mV
Voltage peak to peak	7 mV	9 mV	9 mV	11 mV	16 mV
Current rms	200 mA	100 mA	40 mA	25 mA	12 mA
<b>Readback accuracy at 25° C ±5° C (percent of reading plus fixed)</b>					
Voltage	0.05% + 12 mV	30 mV	50 mV	90 mV	180 mV
±Current	0.1% + 150 mA	100 mA	60 mA	35 mA	18 mA
<b>Load regulation</b>					
Voltage	0.002%+ 300 µV	650 µV	1.2 mV	2 mV	4 mV
<b>Line regulation</b>					
Current	0.005%+ 10 mA	7 mA	4 mA	2 mA	1 mA

**Transient response time** Less than 900 µs for the output voltage to recover 100 mV following a change in load from 100% to 50% or 50% to 100% of the output current rating of the supply

**Supplemental Characteristics** (Non-warranted characteristics determined by design and useful in applying the product)

<b>Average resolution</b>					
Voltage	2 mV	5 mV	10 mV	15 mV	30 mV
Current	55 mA	25 mA	15 mA	8.75 mA	4.5 mA
OVP	15 mV	35 mV	65 mV	100 mV	215 mV
<b>Output Voltage programming response time*</b>					
(excluding command processing time)	30 ms	60 ms	130 ms	130 ms	195 ms

\* Full load programming rise/fall time (10% to 90% or 90% to 10%) with full resistive load equal to rated output voltage/rated output current.



## Single-Output: 2000 W GPIB (Continued)

### Supplemental Characteristics for all model numbers

**dc Floating Voltage:** Output terminals can be floated up to  $\pm 240$  Vdc from chassis ground

**Output Common-Mode Noise Current:** (to signal ground binding post) 500  $\mu$ A rms, 4 mA peak-to-peak

**Remote Sensing:** Up to half the rated output voltage can be dropped in each load lead. The drop in the load leads subtracts from the voltage available for the load.

**Command Processing Time:** Average time required for the output voltage to begin to change following receipt of digital data is 20 ms for the power supplies connected directly to the GPIB.

**Modulation:** (Analog programming of output voltage and current)

**Input Signal:** 0 to -4 V for voltage, 0 to 7 V for current

**Input Impedance:** 60 k Ohm or greater

**Input Power:** 3,800 VA, 2,600 W at full load; 170 W at no load

**GPIB Interface Capabilities:** SH1, AH1, T6, L4, SR1, RL1, PP0, DC1, DT1, E1, and C0. IEEE-488.2 and SCPI-compatible command set

**Regulatory Compliance:** Listed to UL1244; certified to CSA556B; conforms to IEC 61010-1.

**Size:** 425.5 mm W x 132.6 mm H x 640 mm D (16.75 in x 5.22 in x 25.2 in)  
See page 102 for more details

**Weight:** Net, 28.2 kg (62 lbs); shipping, 31.8 kg (70 lbs)

**Warranty Period:** One year

Specifications (at 0° to 55° C unless otherwise specified)	6671A-J03 Special Order Option	6671A-J04 Special Order Option	6671A-J17 Special Order Option	6672A-J04 Special Order Option	6673A-J03 Special Order Option
<b>Number of outputs</b>	1	1	1	1	1
<b>GPIB</b>	Yes	Yes	Yes	Yes	Yes
<b>Output ratings</b>					
Output voltage	14 V	10 V	15 V	24 V	37.5 V
Output current	150 A	200 A	120 A	85 A	45 A
<b>Programming accuracy at 25° C <math>\pm</math> 5° C</b>					
Voltage 0.04%+	14 mV	10 mV	15 mV	25 mV	37.5 mV
Current 0.1%+	90 mA	125 mA	90 mA	60 mA	40 mA
<b>Ripple and noise</b>					
from 20 Hz to 20 MHz					
Voltage rms	1.5 mV	750 $\mu$ V	1.5 mV	1 mV	800 $\mu$ V
Voltage peak to peak	15 mV	9 mV	15 mV	11 mV	9 mV
Current rms	150 mA	200 mA	150 mA	100 mA	40 mA
<b>Readback accuracy at 25° C <math>\pm</math> 5° C</b> (percent of reading plus fixed) System models only					
Voltage 0.05% +	25 mV	15 mV	27 mV	40 mV	53.5 mV
$\pm$ Current 0.1% +	110 mA	150 mA	110 mA	100 mA	60 mA
<b>Load regulation</b>					
Voltage 0.002%+	600 $\mu$ V	300 $\mu$ V	650 $\mu$ V	650 $\mu$ V	1.2 mV
<b>Line regulation</b>					
Current 0.005%+	7 mA	10 mA	7 mA	7 mA	4 mA
<b>Transient response time</b>	Less than 900 $\mu$ s for the output voltage to recover 100 mV following a change in load from 100% to 50% or 50% to 100% of the output current rating of the supply				
<b>Supplemental Characteristics</b>	(Non-warranted characteristics determined by design and useful in applying the product)				
<b>Average resolution</b>					
Voltage	4 mV	2.5 mV	4 mV	6 mV	10 mV
Current	40 mA	55 mA	35 mA	22 mA	15 mA
OVP	28 mV	20 mV	30 mV	42 mV	65 mV
<b>Output Voltage programming response time*</b>					
(excluding command programming processing time)	30 ms	35 ms	35 ms	70 ms	130 ms

\* Full load programming rise/fall time (10% to 90% or 90% to 10%) with full resistive load equal to rated output voltage/rated output current.



## Single-Output: 2000 W GPIB (Continued)

### Ordering Information

**Opt 200** 174 to 220 Vac, 47 to 63 Hz (Japan only)

**Opt 230** 191 to 250 Vac, 47 to 63 Hz

\* **Opt 908** Rack-mount Kit (p/n 5062-3977)

\* **Opt 909** Rack-mount Kit w/handles (p/n 5063-9221)

**Opt 0L2** Extra Standard Documentation Package

**Opt 0B3** Service Manual

**Opt 0B0** No documentation package

\* Support rails required

### Accessories

p/n 1494-0059 Accessory Slide Kit

p/n 1252-3698 7-pin Analog Plug

p/n 1252-1488 4-pin Digital Plug

p/n 5080-2148 Serial Link Cable 2 m (6.6 ft)

E3663AC Support rails for Agilent rack cabinets

Specifications (at 0° to 55° C unless otherwise specified)	6673A-J08 Special Order Option	6674A-J03 Special Order Option	6674A-J07 Special Order Option	6675A-J04 Special Order Option	6675A-J06 Special Order Option
<b>Number of outputs</b>	1	1	1	1	1
<b>GPIB</b>	Yes	Yes	Yes	Yes	Yes
<b>Output ratings</b>					
Output voltage	40 V	56 V	50 V	160 V	135 V
Output current	50 A	38 A	42 A	13 A	16 A
<b>Programming accuracy at 25° C ±5° C</b>					
Voltage	0.04%+	40 mV	60 mV	60 mV	160 mV
Current	0.1%+	35 mA	28 mA	30 mA	10 mA
<b>Ripple and noise</b>					
from 20 Hz to 20 MHz					
Voltage rms	1 mV	1.25 mV	1.25 mV	2.8 mV	2 mV
Voltage peak to peak	10.5 mV	11 mV	11 mV	20 mV	18 mV
Current rms	40 mA	28 mA	25 mA	18 mA	12 mA
<b>Readback accuracy at 25° C ±5° C</b> (percent of reading plus fixed) System models only					
Voltage	0.05%+	60 mV	90 mV	90 mV	240 mV
±Current	0.1%+	60 mA	38 mA	42 mA	14 mA
<b>Load regulation</b>					
Voltage	0.002%+	1.4 mV	2 mV	2 mV	6 mV
<b>Line regulation</b>					
Current	0.005%+	4 mA	2 mA	2 mA	1 mA
<b>Transient response time</b>	Less than 900 µs for the output voltage to recover 100 mV following a change in load from 100% to 50% or 50% to 100% of the output current rating of the supply				
<b>Supplemental Characteristics</b>	(Non-warranted characteristics determined by design and useful in applying the product)				
<b>Average resolution</b>					
Voltage	10.5 mV	14 mV	12 mV	40 mV	34 mV
Current	12.5 mA	9.5 mA	11 mA	3.25 mA	4 mA
OVP	75 mV	100 mV	85 mV	300 mV	242 mV
<b>Output Voltage programming response time*</b>					
(excluding command programming processing time)	130 ms	130 ms	130 ms	280 ms	250 ms

\* Full load programming rise/fall time (10% to 90% or 90% to 10%) with full resistive load equal to rated output voltage/rated output current.



## Single-Output: 2000 W GPIB (Continued)

Specifications (at 0° to 55° C unless otherwise specified)	6675A-J07 Special Order Option	6675A-J08 Special Order Option	6675A-J09 Special Order Option	6675A-J11 Special Order Option
<b>Number of outputs</b>	1	1	1	1
<b>GPIB</b>	Yes	Yes	Yes	Yes
<b>Output ratings</b>				
Output voltage	200 V	100 V	110 V	150 V
Output current	11 A	22 A	20 A	15 A
<b>Programming accuracy at 25° C ±5° C</b>				
Voltage 0.04%+	200 mV	120 mV	120 mV	150 mV
Current 0.1%+	8 mA	15 mA	13.5 mA	11 mA
<b>Ripple and noise</b>				
from 20 Hz to 20 MHz				
Voltage rms	3.5 mV	1.9 mV	1.9 mV	2.5 mV
Voltage peak to peak	25 mV	16 mV	16 mV	18 mV
Current rms	15 mA	15 mA	13.5 mA	12 mA
<b>Readback accuracy at 25° C ±5° C (percent of reading plus fixed) System models only</b>				
Voltage 0.05%+	300 mV	180 mV	180 mV	225 mV
±Current 0.1%+	12 mA	22 mA	20 mA	15 mA
<b>Load regulation</b>				
Voltage 0.002% +	7 mV	4 mV	4 mV	6 mV
<b>Line regulation</b>				
Current 0.005% +	1 mA	4 mV	4 mV	1 mA
<b>Transient response time</b>	Less than 900 μs for the output voltage to recover 100 mV following a change in load from 100% to 50% or 50% to 100% of the output current rating of the supply			
<b>Supplemental Characteristics</b>	(Non-warranted characteristics determined by design and useful in applying the product)			
<b>Average resolution</b>				
Voltage	50 mV	30 mV	30 mV	37.5 mV
Current	2.75 mA	4.5 mA	4.5 mA	3.75 mA
OVP	360 mV	215 mV	215 mV	270 mV
<b>Output Voltage programming response time*</b>				
(excluding command programming processing time)	350 ms	195 ms	195 ms	250 ms

\* Full load programming rise/fall time (10% to 90% or 90% to 10%) with full resistive load equal to rated output voltage/rated output current.

### Your Requested Excerpt from the Agilent Power Products Catalog

The preceding page(s) are an excerpt from the *2002-2003 Power Products Catalog*.

We hope that these pages supply the information that you currently need.

If you would like to have further information about the extensive selection of Agilent dc power supplies, ac sources, and dc electronic loads, please visit [www.agilent.com/find/power](http://www.agilent.com/find/power) to print a copy of the complete Power Products catalog, or to request that a copy be sent to you. You will also find a lot of other useful information on this web site.

In the full Power Products Catalog, you will find that Agilent offers much more than basic power generation. If you need basic, clean, power for your lab bench, it's there. But in each product category, we've also integrated the capabilities that you need for a complete power solution, including extensive measurement and analysis capabilities.

Please give us a call at your local Agilent Technologies sales office, or call a regional office listed below, for assistance in choosing or using Agilent power products.

### Keep up to date with Agilent's Test and Measurement Email Updates

As an Email Update subscriber, you will receive periodic customized email updates that match the areas of interest that you have specified. Your update will include products and services, applications and support information, events, and promotions. Sign up today at [www.agilent.com/find/emailupdates](http://www.agilent.com/find/emailupdates).

Check off dc power supplies, ac power sources or electronic loads on your registration form, and we will promptly let you know what's new in power products! Our Privacy Statement at [www.agilent.com/go/privacy](http://www.agilent.com/go/privacy) describes our commitment to you regarding your privacy.

To see a copy of the user's guide, please visit our Web site at [www.agilent.com/find/manuals](http://www.agilent.com/find/manuals)

By internet, phone, or fax, get assistance with all your test & measurement needs

Online assistance:  
[www.agilent.com/find/assist](http://www.agilent.com/find/assist)

### Phone or Fax

**United States:**  
(tel) 1 800 829 4444

**Canada:**  
(tel) 1 877 894 4414  
(fax) (905) 282-6495

**China:**  
(tel) 800-810-0189  
(fax) 1-0800-650-0121

**Europe:**  
(tel) (31 20) 547 2323  
(fax) (31 20) 547 2390

**Japan:**  
(tel) (81) 426 56 7832  
(fax) (81) 426 56 7840

**Korea:**  
(tel) (82-2) 2004-5004  
(fax) (82-2) 2004-5115

**Latin America:**  
(tel) (305) 269 7500  
(fax) (305) 269 7599

**Taiwan:**  
(tel) 080-004-7866  
(fax) (886-2) 2545-6723

**Other Asia Pacific Countries:**  
(tel) (65) 375-8100  
(fax) (65) 836-0252  
Email: [tm\\_asia@agilent.com](mailto:tm_asia@agilent.com)

Product specifications and descriptions in this document subject to change without notice.



**Agilent Technologies**