

Product Description:

Agilent 6235A Triple Output DC Power Supply

Performance Characteristics of the 6235A

Form Factor	Benchtop
No. of Outputs	3 o/p
Range programming modes	Auto
Output 1 Max. power	6 Watts
Output 1/Range 1 Max. Current	1 A (0 V to 6 V)
Output 2 Max. power	3.6 Watts
Output 2/Range 1 Max. Current	0.2 A (0 V to 18 V)
Output 3 Max. Power	3.6 Watts
Output 3/Range 1 Max. Current	0.2 A (0 V to -18 V)
Voltage Ripple and Noise	.001 uV
Load Regulation, Voltage	10 mV
Line Regulation, Voltage	15 mV
Remote Sensing Measurement	No
Multiple Unit Combinations	Parallel, Series
Overvoltage Protection	Yes
Overcurrent Protection	Yes
Over-temperature Protection	No
Local Lockout	No
Self test	No

Programmability/Connectivity of the 6235A

User Interface	Proprietary
----------------	-------------

6235A Life Cycle Data

Out of Production	Feb-01-1995
Out of Support	Sep-01-2000

6235A Compliance

CE Compliance	Not on file
UL Compliance	Compliant

6235A Power Requirements

Input Power	USA (110V/60Hz)
-------------	-----------------

6235A Physical Dimensions

Width: (N/A)

Height: 89 mm(3.5 in)

Length: 210 mm(8.26 in)

Weight: 2.3 kg(5.07 lb)